

| TRANSISTOR NUMBER | PM OA LT | PACK-AGE | LEAD INFO | VCB MAX | VCE MAX | VEB MAX | I C MAX | T J MAX | P TOT | F T MIN | C OB MAX | H FE | H FE BIAS | USE | MFR | EUR EQUIV | USA EQUIV | ISS |
|-------------------|----------|----------|-----------|---------|---------|---------|---------|---------|--------|---------|----------|--------|-----------|-----|-----|-----------|-----------|-----|
| 2N3571 | NS | T072 | L06 | 25V | 15V | 3V | 50MA | 200C | 200MWF | 1200M | DP85 | 20/200 | 5MA | ULA | SEU | | | 0 |
| 2N3572 | NS | T072 | L06 | 25V | 13V | 3V | 50MA | 200C | 200MWF | 1000M | DP85 | 20/300 | 2MA | ULA | SEU | | | 0 |
| 2N3576 | PS | T018 | L01 | 20V | 15V | 5V | 200MA | 200C | 360MWF | 400M | 4P5 | 40/120 | 10MA | VLS | MOB | BSW25 | 2N3546 | 0 |
| 2N3577 | NS | X51 | X51 | 100V | 80V | | 2A | 175C | 85WC | 10M | | 12/60 | 1A | AMH | OBS | | | 2 |
| 2N3579 | PS | T046 | L01 | 60V | 60V | | 30MA | 200C | 400MWF | 80M | 6P | 30/120 | 1MA | ALG | OBS | BC107 | 2N2510 | 2 |
| 2N3580 | PS | T046 | L01 | 60V | 60V | | 30MA | 200C | 400MWF | 80M | 6P | 60/240 | 1MA | ALG | OBS | BC107 | 2N2510 | 2 |
| 2N3581 | PS | T046 | L01 | 50V | 40V | | 30MA | 200C | 400MWF | 30M | 6P | 50/150 | 100UA | ALN | OBS | BC107C | 2N2484 | 2 |
| 2N3582 | PS | T046 | L01 | 50V | 40V | | 30MA | 200C | 400MWF | 30M | 6P | 100MN | 100UA | ALN | OBS | BC107C | 2N2484 | 2 |
| 2N3583 | NS | T066 | L43 | 250V | 175V | 6V | 1A | 200C | 35WC | 10M | | 40/200 | 500MA | RME | SAS | | | 1 |
| 2N3584 | NS | T066 | L43 | 375V | 250V | 6V | 2A | 200C | 35WC | 10M | | 25/100 | 1A | RHE | TIB | | | 1 |
| 2N3585 | NS | T066 | L43 | 500V | 300V | 6V | 2A | 200C | 35WC | 10M | | 25/100 | 1A | RHE | TIB | | | 1 |
| 2N3588 | PG | T072 | L06 | 25V | | | 10MA | 85C | 100MWF | 200M | | 20MN | 1MA | ULA | OBS | AF239 | 2N3783 | 2 |
| 2N3589 | NS | T05F | L44 | 200V | | | 500MA | 175C | 2WC | 15M | | 30/90 | 200MA | AME | OBS | | | 2 |
| 2N3590 | NS | T05F | L44 | 200V | | | 500MA | 175C | 2WC | 15M | | 75/150 | 200MA | AME | OBS | | | 2 |
| 2N3591 | NS | T012 | L09 | 200V | | | 500MA | 175C | 1WF | 15M | | 30/90 | 200MA | AME | OBS | | | 2 |
| 2N3592 | NS | T012 | L09 | 200V | | | 500MA | 175C | 1WF | 15M | | 75/150 | 200MA | AME | OBS | | | 2 |
| 2N3593 | NS | T0102 | L59 | 200V | | | 500MA | 175C | 1WF | 15M | | 30/90 | 200MA | AME | OBS | | | 2 |
| 2N3594 | NS | T0102 | L59 | 200V | | | 500MA1 | 75C | 1WF | 15M | | 75/150 | 200MA | AME | OBS | | | 2 |
| 2N3595 | NS | T0102 | L59 | 200V | | | 500MA | 175C | 1.5WF | 15M | | 30/90 | 200MA | AME | OBS | | | 2 |
| 2N3596 | NS | T0102 | L59 | 200V | | | 500MA | 175C | 1.5WF | 15M | | 75/150 | 200MA | AME | OBS | | | 2 |
| 2N3597 | NS | T063 | L60 | 60V | 40V | | 20A | 200C | 100WC | 30M | 700P | 40/120 | 10A | RHG | OBS | BLX28 | 2N5966 | 2 |
| 2N3598 | NS | T063 | L60 | 80V | 60V | | 20A | 200C | 100WC | 30M | 700P | 40/120 | 10A | RHG | OBS | BLX28 | 2N5966 | 2 |
| 2N3599 | NS | T063 | L60 | 100V | 80V | | 20A | 200C | 100WC | 30M | 700P | 40/120 | 10A | RHG | OBS | BLX28 | 2N5966 | 2 |
| 2N3600 | NS | T072 | L06 | 30V | 15V | 3V | 50MA | 200C | 200MWF | 850M | 1P7 | 20/150 | 3MA | ULA | NAT | BFY90 | 2N5852 | 2 |
| 2N3601 | PG | T05 | L04 | 100V | 40V | | 3A5 | 100C | 500MWF | 20M | | 60/180 | 1A | RHG | OBS | | 2N2667 | 2 |
| 2N3602 | PG | X26 | L59 | 100V | 40V | | 3A5 | 100C | 750MWF | 20M | | 60/180 | 1A | RHG | OBS | | 2N2670 | 2 |
| 2N3603 | PG | T05 | L04 | 130V | 55V | | 3A5 | 100C | 500MWF | 20M | | 60/180 | 1A | RHG | OBS | | 2N2667 | 2 |
| 2N3604 | PG | X26 | L59 | 130V | 55V | | 3A5 | 100C | 750MWF | 20M | | 60/180 | 1A | RHG | OBS | | 2N2670 | 2 |
| 2N3605 | NS | T098 | L21 | 18V | 14V | 5V | 200MA | 150C | 200MWF | 300M | 6P | 30MN | 10MA | VLS | SEU | BSX20 | 2N2369 | 2 |
| 2N3605A | NS | T098 | L21 | 18V | 14V | 5V | 200MA | 120C | 320MWF | 300M | 6P | 30MN | 10MA | VLS | OBS | BSX20 | 2N2369 | 2 |
| 2N3606 | NS | T098 | L21 | 18V | 14V | 5V | 200MA | 150C | 200MWF | 300M | 6P | 30MN | 10MA | VLS | SEU | BSX20 | 2N2369 | 2 |
| 2N3606A | NS | T098 | L21 | 18V | 14V | 5V | 200MA | 120C | 320MWF | 300M | 6P | 30MN | 10MA | VLS | OBS | BSX20 | 2N2369 | 2 |
| 2N3607 | NS | T098 | L21 | 18V | 14V | 5V | 200MA | 150C | 200MWF | 300M | 6P | 30MN | 10MA | VLS | SEU | BSX20 | 2N2369 | 2 |
| 2N3611 | PG | T03 | L05 | 40V | 25V | 20V | 15A | 110C | 77WC | 300K | | 35/70 | 3A | AHG | MOB | ASZ16 | 2N1536 | 0 |
| 2N3612 | PG | T03 | L05 | 60V | 35V | 30V | 15A | 110C | 77WC | 300K | | 35/70 | 3A | AHG | MOB | ASZ16 | 2N1536 | 0 |
| 2N3613 | PG | T03 | L05 | 40V | 25V | 20V | 15A | 110C | 77WC | 300K | | 60/120 | 3A | AHG | MOB | ASZ16 | 2N1536 | 0 |
| 2N3614 | PG | T03 | L05 | 60V | 35V | 30V | 15A | 110C | 77WC | 300K | | 60/120 | 3A | AHG | MOB | ASZ16 | 2N1536 | 0 |
| 2N3615 | PG | T03 | L05 | 80V | 50V | 40V | 15A | 110C | 77WC | 300K | | 30/60 | 3A | AHH | MOB | ASZ15 | 2N1533 | 0 |
| 2N3616 | PG | T03 | L05 | 100V | 75V | 50V | 15A | 110C | 77WC | 300K | | 30/60 | 3A | AHH | MOB | ASZ15 | 2N1533 | 0 |
| 2N3617 | PG | T03 | L05 | 80V | 50V | 40V | 15A | 110C | 77WC | 300K | | 45/90 | 3A | AHH | MOB | ASZ15 | 2N1533 | 0 |
| 2N3618 | PG | T03 | L05 | 100V | 75V | 50V | 15A | 110C | 77WC | 300K | | 45/90 | 3A | AHH | MOB | ASZ15 | 2N1533 | 0 |
| 2N3619 | NS | T05 | L04 | 75V | 40V | | 2A5 | 175C | 7.5WC | 200M | 50P | 40MN | 1A | RHG | OBS | BSV64 | 2N4877 | 2 |
| 2N3620 | NS | T0102 | L59 | 75V | 40V | | 5A | 175C | 7.5WC | 200M | 50P | 40MN | 1A | RHG | OBS | | | 2 |
| 2N3621 | NS | T061 | L46 | 75V | 40V | | 10A | 175C | 30WC | 200M | 50P | 40MN | 1A | RHG | OBS | BDY63 | 2N5304 | 2 |
| 2N3622 | NS | T061 | L46 | 75V | 40V | | 10A | 175C | 30WC | 200M | 50P | 40MN | 1A | RHG | OBS | BDY63 | 2N5304 | 2 |
| 2N3623 | NS | T05 | L04 | 75V | 40V | | 2A5 | 175C | 7.5WC | 200M | 50P | 40MN | 1A | RHG | OBS | BSV64 | 2N4877 | 2 |
| 2N3624 | NS | T0102 | L59 | 75V | 40V | | 5A | 175C | 7.5WC | 200M | 50P | 40MN | 1A | RHG | OBS | | | 2 |
| 2N3625 | NS | T061 | L46 | 75V | 40V | | 10A | 175C | 30WC | 200M | 50P | 40MN | 1A | RHG | OBS | BDY63 | 2N5304 | 2 |
| 2N3626 | NS | T061 | L46 | 75V | 40V | | 10A | 175C | 30WC | 200M | 50P | 40MN | 1A | RHG | OBS | BDY63 | 2N5304 | 2 |
| 2N3627 | NS | T05 | L04 | 100V | 50V | | 2A5 | 175C | 7.5WC | 200M | 50P | 40MN | 1A | RHG | OBS | BSV64 | 2N4877 | 2 |
| 2N3628 | NS | T0102 | L59 | 100V | 50V | | 5A | 175C | 7.5WC | 200M | 50P | 40MN | 1A | RHG | OBS | | | 2 |
| 2N3629 | NS | T061 | L46 | 100V | 50V | | 10A | 175C | 30WC | 200M | 50P | 40MN | 1A | RHG | OBS | BDY63 | 2N5304 | 2 |
| 2N3630 | NS | T061 | L46 | 100V | 50V | | 10A | 175C | 30WC | 200M | 50P | 40MN | 1A | RHG | OBS | BDY63 | 2N5304 | 2 |
| 2N3632 | NS | T060 | L61 | 65V | 40V | 4V | 3A | 200C | 23WC | 200M | 20P | 10MN | 250MA | UMP | MOB | | | 0 |
| 2N3633 | NS | T018 | L01 | 15V | 6V | | 50MA | 200G | 300MWF | 1300M | 2P5 | 50/150 | 10MA | SLS | OBS | | 2N3960 | 2 |
| 2N3634 | PS | T05 | L04 | 140V | 140V | 5V | 1A | 200C | 1WF | 150M | 10P | 50/150 | 50MA | AME | MOB | | 2N3637 | 2 |
| 2N3634S | PS | T039 | L04 | 140V | 140V | 5V | 1A | 200C | 1WF | 150M | 10P | 50/150 | 50MA | AME | MOB | BFT19 | 2N3634 | 2 |
| 2N3635 | PS | T05 | L04 | 140V | 140V | 5V | 1A | 200C | 1WF | 200M | 10P | 100MN | 50MA | AME | MOB | | 2N3637 | 2 |
| 2N3635S | NS | T039 | L04 | 140V | 140V | 5V | 1A | 200C | 1WF | 200M | 10P | 100MN | 50MA | AME | MOB | | 2N3637 | 2 |
| 2N3636 | PS | T05 | L04 | 175V | 175V | 5V | 1A | 200C | 1WF | 150M | 10P | 50/150 | 50MA | AME | MOB | | 2N3637 | 2 |
| 2N3636S | PS | T039 | L04 | 175V | 175V | 5V | 1A | 200C | 1WF | 150M | 10P | 50/150 | 50MA | AME | MOB | BFT19A | 2N3636 | 2 |
| 2N3637 | PS | T05 | L04 | 175V | 175V | 5V | 1A | 200C | 1WF | 200M | 10P | 100MN | 50MA | AME | MOB | | 2N3637 | 2 |
| 2N3637S | PS | T039 | L04 | 175V | 175V | 5V | 1A | 200C | 1WF | 200M | 10P | 100MN | 50MA | AME | MOB | | 2N3637 | 2 |
| 2N3638 | PS | T0105 | L04 | 25V | 25V | 4V | 500MA | | 300MWF | 100M | 20P | 30MN | 50MA | AMG | SGI | BFS95 | 2N4036 | 0 |
| 2N3638A | PS | T0105 | L04 | 25V | 25V | 4V | 500MA | 125C | 300MWF | 150M | 10P | 100MN | 10MA | RMG | SGI | BFX29 | 2N2905A | 0 |
| 2N3639 | PS | T0105 | L04 | 6V | 6V | 4V | 80MA | 125C | 200MWF | 500M | 3P5 | 30/120 | 10MA | VLS | FCU | BSW25 | 2N3546 | 0 |
| 2N3640 | PS | T0105 | L04 | 12V | 12V | 4V | 80MA | 125C | 200MWF | 500M | 3P5 | 30/120 | 10MA | VLS | FCU | BSW25 | 2N3546 | 0 |
| 2N3641 | NS | T0105 | L04 | 60V | 30V | 5V | 500MA | 125C | 350MWF | 250M | 8P | 40/120 | 150MA | AMG | SGI | BSW54 | 2N2219A | 0 |
| 2N3642 | NS | T0105 | L04 | 60V | 45V | 5V | 500MA | 125C | 350MWF | 150M | 8P | 40/120 | 150MA | AMG | FCU | BFY50 | 2N2297 | 0 |
| 2N3643 | NS | T0105 | L04 | 60V | 30V | 5V | 500MA | 125C | 350MWF | 250M | 8P | 100MN | 150MA | RMG | SGI | BSW54 | 2N2219A | 0 |
| 2N3644 | PS | T0105 | L04 | 45V | 45V | 5V | 500MA | 125C | 300MWF | 200M | 8P | 115MN | 50MA | RMG | SGI | BFX29 | 2N2905A | 0 |
| 2N3645 | PS | T0105 | L04 | 60V | 60V | 5V | 500MA | 125C | 300MWF | 200M | 8P | 115MN | 50MA | RMH | SGI | BFX29 | 2N2905A | 0 |
| 2N3646 | NS | T0106 | L17 | 40V | 15V | 5V | 200MA | 125C | 200MWF | 350M | 5P | 30/120 | 30MA | RLS | SGI | BSX20 | 2N2369 | 0 |
| 2N3647 | NS | T046 | L01 | 40V | 10V | 6V | 500MA | 200C | 400MWF | 350M | 4P | 25/150 | 150MA | VLS | MOB | BSX20 | 2N2369 | 0 |
| 2N3648 | NS | T046 | L01 | 40V | 15V | 6V | 500MA | 200C | 400MWF | 450M | 4P | 30/120 | 150MA | VLS | MOB | BSX20 | 2N2369 | 0 |